

## PRODUCT SUMMARY

ConcealFab's Hexagonal Shroud is designed to conceal 2 or 3 Ericsson 1281 radios in a 120° or 180° configuration in the middle of an existing pole. For a complete color match, vinyl wrap is included for 3 radios and can be applied to the radio's radome in the field.

The hexagonal shroud will fit a pole with a 4" to 9" diameter range and is trimmed in the field to match the pole diameter it will be mounted on. Each radio requires a fan kit (900958) that is sold separately.



www.cf-pat.com



\*RF equipment not included

## SPECIFICATIONS

<b>PART NUMBER</b>	900889
<b>DESCRIPTION</b>	Hexagonal Shroud, Ericsson 1281
<b>RADIO COMPATIBILITY</b>	3X Ericsson 1281
<b>APPROVED FREQUENCIES</b>	25 GHz - 40 GHz
<b>MOUNTING OPTIONS</b>	Banded
<b>POLE DIAMETER RANGE</b>	4" - 9"
<b>MATERIAL</b> structural components	304 Stainless Steel & ABS Plastic
<b>MAXIMUM WIND SPEED</b>	90 MPH
<b>THERMAL MANAGEMENT</b>	Active
<b>VOLUME</b>	6.25 ft <sup>3</sup>
<b>APPROXIMATE WEIGHT</b> without RF equipment	36.83 lbs

## COLOR OPTIONS

<b>Jet Black-001</b>	<b>Terra Brown-002</b>	<b>Light Gray-003</b>	<b>Silver-004</b>	<b>Black Green-021</b>	<b>Tan-040</b>
RAL 9005	RAL 8028	RAL 7035	FED STD 36463	RAL 6012	FDR STD 30340

\*Light Gray - 003 matches light concrete or aluminum poles  
\*Silver - 004 matches galvanized steel poles

**ASK ABOUT OUR CUSTOM COLOR OPTIONS**

*There may be minor differences between color options and finished goods due to formulation variations.*